



LIST OF REPLACEMENT PARTS

PART NO.	LIST OF REPLACEMENT PARTS	PART NO.	LIST OF REPLACEMENT PARTS
701852-1	PRINTED CIRCUIT BOARD W/PARTS	230230-1219	RESISTOR 120 OHM 10% .5W
300727-1	TRANSFORMER POWER 120V	230230-1239	RESISTOR 12K OHM 10% .5W
300727-2	TRANSFORMER POWER 240V	230230-2229	RESISTOR 2.2K OHM 10% .5W
180865-1050	FUSE .5 AMP 250V	230230-2239	RESISTOR 22K OHM 10% .5W
180865-1025	FUSE .25 AMP 250V (240V MODELS)	230230-2749	RESISTOR 270K OHM 10% .5W
160804-10	SWITCH POWER	230230-3349	RESISTOR 330K OHM 10% .5W
181572-4	LIGHT PILOT	230230-4709	RESISTOR 47 OHM 10% .5W
181573-2	JACK J202	230230-4719	RESISTOR 470 OHM 10% .5W
181573-3	JACK J201	230230-4729	RESISTOR 4700 OHM 10% .5W
461521-3	A.C. CORD (120V)	230230-4739	RESISTOR 47K OHM 10% .5W
461533-1	A.C. CORD (240V)	230231-1099	RESISTOR 1 OHM 10% 1W
142901-1	ENOB	230231-1819	RESISTOR 180 OHM 10% 1W
121474-1	HANDLE	230231-2209	RESISTOR 22 OHM 10% 1W
142911-3	LOGO	230230-8229	RESISTOR 8.2K OHM 10% .5W
151526-1	NAMEPLATE (120V)	250552-1019	CAPACITOR 100 PF 10%
151526-2	NAMEPLATE (240V)	250581-1053	CAPACITOR .1 MFD 10%
400826-1	CLOTH GRILLE	250581-2253	CAPACITOR .22 MFD 10%
400827-3	VINYL	250581-4733	CAPACITOR .0047 MFD 10%
580173-1	SPEAKER (SPECIAL)	250581-4743	CAPACITOR .047 MFD 10%
142935-1	OVERLAY	250581-4753	CAPACITOR .47 MFD 10%
591770-1	SCHEMATIC	270117-1116	CAPACITOR 10 MFD 16V
701853-1	CABINET (COVERED)	270117-1235	CAPACITOR 100 MFD 35V
103497-2	SCREW #10-32 x 1 FOR HANDLE	270117-1350	CAPACITOR 1000 MFD 50V
610149-1	TRANSISTOR POWER Q5	270117-5250	CAPACITOR 47 MFD 50V
610149-2	TRANSISTOR POWER Q6	270117-5325	CAPACITOR 470 MFD 25V
210830-1	PRINTED CIRCUIT BOARD	530135-2	DIODE BLAS D5
220663-5	CONTROL VOLUME 50K	530171-1	DIODE SILICON D1,2,3,4
220663-6	CONTROL 100K BASS & TREBLE	610083-1	TRANSISTOR Q2
230230-1029	RESISTOR 1000 OHM 10% .5W	610094-1	TRANSISTOR Q1
230230-1039	RESISTOR 10K OHM 10% .5W	610142-3	TRANSISTOR NPN Q3
230230-1049	RESISTOR 100K OHM 10% .5W	610153-1	TRANSISTOR NPN Q4
230230-1205	RESISTOR 12 OHM 5% .5W	181572-7	LIGHT PILOT 240V

NOTES:

1. -DC VOLTAGE READINGS WITH NO SIGNAL APPLIED, USING A 20,000 OHM PER-VOLT VOLTMETER.
2. -CIRCUIT OF CHASSIS MAY VARY SLIGHTLY FROM THAT SHOWN HERE DUE TO NORMAL PRODUCTION CHANGES.
3. -A.C. VOLTAGES ARE ENCLOSED WITH BOXES.
4. -MAGNAVOX PART NO'S ARE SPECIFIED IN PARENTHESIS.
5. -* EXPORT VERSION ONLY.

A RELEASED ANI450 3-19-76		591770-1	
ADDITIONAL SPECIFICATIONS		REVISIONS	
MATERIAL		SIZE- 6.75 X 5.00	
UNLESS OTHERWISE SPECIFIED		THE AMPEG COMPANY	
DECIMALS (FRACTIONS) ±TOL.		DIVISION OF THE MAGNAVOX COMPANY	
3/8 .000 1/16 ±.004		P.O. BOX 183 GARDEN, N.J. 07030	
3/16 .000 1/32 ±.002		SCHEMATIC (DESCRIPTION OF PARTS)	
1/8 .000 1/64 ±.001			
TOLERANCES - CLASS 1		DATE	DRW. NO.
DIMENSIONS IN INCHES UNLESS OTHERWISE SPECIFIED ON DRAWING		3-19-76	6-18
DO NOT SCALE DRAWING		APP. <i>[Signature]</i>	SCALE
THIS MATERIAL IS THE PROPERTY OF AND PROPRIETARY TO THE MAGNAVOX COMPANY AND IS NOT TO BE DISCLOSED TO OTHERS OR USED FOR OTHER THAN AUTHORIZED MAGNAVOX PURPOSES WITHOUT THE WRITTEN PERMISSION OF THE MAGNAVOX COMPANY. THIS MATERIAL MUST BE RETURNED TO THE MAGNAVOX COMPANY WHEN THE HOLDER NO LONGER REQUIRES ITS USE FOR AUTHORIZED MAGNAVOX PURPOSES.		SIZE	DRW. NO.
		C	591770

591770